


This exam consists of five exercises. The available points for each item are written in the margin. You need at least 50 points to pass. **Explain your answers to the first four exercises!**

- [1] Consider the boolean function $f(x, y, z) = (x \oplus y) + z$ and the BDD B_g



- [7] (a) Starting from B_g , compute a reduced OBDD that is equivalent to $\exists y.g$.
- [6] (b) Compute the algebraic normal forms of f and g .
- [7] (c) Determine which of the five properties from Post's adequacy theorem hold for f . Which of the three sets $\{f, \neg\}$, $\{\bar{f}\}$ and $\{f, 1\}$ are adequate?

- [6] [2] (a) Use Tseitin's transformation to compute an equisatisfiable CNF of the propositional formula

$$\varphi = q \vee (p \rightarrow s) \rightarrow \neg p \vee s$$

- [7] (b) Use DPLL with first decision $\overset{d}{p}$ to determine satisfiability of

$$\psi = (p \vee s) \wedge (p \rightarrow \neg q) \wedge (\neg q \rightarrow r) \wedge (\neg p \vee \neg r \vee s) \wedge (q \vee \neg r \vee \neg s)$$


- [7] (c) Use resolution to determine satisfiability of the following clausal form, where a is a constant and x is a variable:

$$\{\{P(f(f(a)))\}, \{\neg P(x), Q(x)\}, \{P(x), R(f(x))\}, \{\neg Q(f(a))\}, \{\neg Q(x), \neg R(x)\}\}$$

- [3] For each of the following sequents, either give a natural deduction proof or find a model which does not satisfy it.

- [6] (a) $\vdash p \vee (p \rightarrow q)$
- [7] (b) $\forall x (\exists y R(x, y) \rightarrow \neg R(x, x)), \exists x \forall y R(y, x) \vdash \forall x \neg R(x, x)$
- [7] (c) $\forall x \exists y (R(x, y) \wedge P(y)), \exists x \neg R(x, x) \vdash \neg \forall x \forall y (P(x) \wedge P(y) \rightarrow x = y)$

4 Consider the following model $\mathcal{M}$:



[6] (a) Determine in which states of $\mathcal{M}$ the CTL formula

$$\varphi = E[EG q \wedge EX \neg q \cup AX q]$$

is satisfied by applying the CTL model checking algorithm.

[7] (b) Find a CTL formula ψ such that $\mathcal{M}, 1 \models \psi$ and $\mathcal{M}, 2 \not\models \psi$.

[7] (c) Find an LTL formula χ such that neither $\mathcal{M}, 2 \models \chi$ nor $\mathcal{M}, 2 \models \neg\chi$.

[20] 5 Determine whether the following statements are true or false. Every correct answer is worth 2 points. For every wrong answer 1 point is subtracted, provided the total number of points is non-negative.

statement

$$\llbracket EG \varphi \rrbracket = \llbracket \varphi \rrbracket \cap \text{pre}_{\exists}(\llbracket EG \varphi \rrbracket)$$

The proof rules $\neg\neg$ i and PBC are inter-derivable.

The dual of a monotone boolean function is monotone.

The CTL* formulas $E[XFG \neg p]$ and $\neg A[XGE[Fp]]$ are semantically equivalent.

Every propositional CNF formula is semantically equivalent to a Horn formula.

The clausal form $\{\{p, \neg q\}, \{q, p, r\}, \{\neg r, q\}, \{\neg q\}\}$ has four different resolvents.

The term $f(x, z)$ is free for y in the formula $\forall x (\exists y (x = y \wedge P(x)) \vee \exists z Q(x, z))$.

The formulas $(p \vee q) \wedge (q \rightarrow \neg(r \vee p))$ and $((p \rightarrow q) \rightarrow r) \rightarrow p$ are equisatisfiable.

The CTL formulas $A[\varphi \cup \psi]$ and $AF \psi \wedge \neg E[\neg \psi \cup (\neg \varphi \wedge \neg \psi)]$ are semantically equivalent.

If a set X of boolean functions is not adequate then $\bar{x}$ or $x \oplus y$ is not expressible using functions from X .